# Unisys

Federal Systems Division

DATE:

August 5, 1997

TO:

J. Lohr/311

FROM:

K. Sahu / 300.1

SUBJECT: Radiation Report on: AS58C1001SF

Project:

SMEX/LITE

Job #:

ER61243

Project part #:

AS58C1001SF

ce: T. Miccolis/300.1 A. Sharma/311 OFA Library/300.1

PPM-97-034

A radiation evaluation was performed on AS58C1001SF (1 MEG EEPROM) to determine the total dose tolerance of these parts. A brief summary of the test results is provided below. For detailed information, refer to Figure 1, and Tables I through IV.

The total dose testing was performed using a Co60 gamma ray source. During the radiation testing, five parts (SN's 70, 71, 72, 73, and 75) were irradiated under bias (see Figure 1 for bias configuration) and one part (SN 74) was used as a control sample. The total dose radiation levels were 5.0, 10.0, 15.0, 25.0, 30.0, 50.0, and 100 kRads\*. The dose rate was between 0.125 and 0.625 kRads/hour (0.035 to 0.174Rads/s). See Table II for the radiation schedule. After the 100 kRad irradiation, the parts were annealed under bias for 265 hours at 25°C. After each radiation exposure and the annealing step, the parts were electrically tested according to the test conditions and the specification limits" listed in Table III. The electrical tests included twelve functional tests. These were as follows: 1-3. READ CHECKERBOARD, 4-6. WRITE/READ ONES, 7-9. WRITE/READ ZEROS, 10-12. WRITE/READ CHECKERBOARD.

SN 75 failed the IIL test initially and gave erratic readings in both timing parameters as well as functional tests from 10 to 100 kRads. For comparison, the data for this part is included in Table IV functional tests but it is not included in the parametric or timing tests in the bottom half of the table.

All parts except SN 75 passed all functional tests up to and including 100 kRads. All parts except SN 75 passed all electrical tests initially and on irradiation up to 25 kRads. No significant degradation was observed in any DC or AC parameter.

After the 30 to 100 kRad irradiations, all parts fell marginally below the specification limit of -2.0µA for IIL with readings in the range of -2.3 to -4.8 µA for all. All parts passed all other tests.

The parts were annealed at 25°C for 265 hours and showed some recovery in IIL with SN 73 passing and all other parts in the range of -2.4 to  $-3.0\mu$ A.

Table IV provides a summary of the mean and standard deviation values for each parameter after each irradiation exposure and annealing step.

Any further details about this evaluation can be obtained upon request. If you have any questions, please call me at (301) 731-8954.

The term Rads, as used in this document, means Rads (SiO2). All radiation levels cited are cumulative.

<sup>&</sup>quot;These are manufacturer's pre-irradiation data specification limits. The manufacturer provided no post-irradiation limits at the time these tests were performed.

## ADVISORY ON THE USE OF THIS DOCUMENT

The information contained in this document has been developed solely for the purpose of providing general guidance to employees of the Goddard Space Flight Center (GSFC). This document may be distributed outside GSFC only as a courtesy to other government agencies and contractors. Any distribution of this document, or application or use of the information contained herein, is expressly conditional upon, and is subject to, the following understandings and limitations:

- (a) The information was developed for general guidance only and is subject to change at any time;
- (b) The information was developed under unique GSFC laboratory conditions that may differ substantially from outside conditions;
- (c) GSFC does not warrant the accuracy of the information when applied or used under other than unique GSFC laboratory conditions;
- (d) Either GSFC or the manufacturer should not construe the information as a representation of product performance;
- (e) Neither the United States government nor any person acting on behalf of the United States government assumes any liability resulting from the application or use of the information.




Figure 1. Radiation Bias Circuit for AS58C1001SF (1 MEG EEPROM)

## Notes:

- 1. All resistors 10kΩ±10%, ¼ W min.
- 2. Read Operation: Address = 0AAAA, Output = 55

#### CARDRPT300\330.doc

#### TABLE I. Part Information

Generic Part Numbers:

AS58C1001SF

Part Numbers

AS58C1001SF

Charge Number:

ER61243

Manufacturer:

Austin Semiconductor/Hitachi die

Lot Date Code (LDC):

9646

Quantities Tested:

6

Serial Numbers of Control Sample:

74

Serial Numbers of Radiation Samples:

70, 71, 72, 73, 75

Part Function:

1 MEG EEPROM

Part Technology:

CMOS

Package Style:

32 PIN FLAT PACK

Test Equipment:

S-50

Engineer:

A. Duvalsaint

<sup>\*</sup> The manufacturer for this part guaranteed no radiation tolerance/hardness.

#### C/XRDRPT300/330 doc

## TABLE II. Radiation Schedule for AS58C1001SF

| EVENT   | DATE                 |
|---|----------------------|
| 1) INITIAL ELECTRICAL MEASUREMENTS  | 06/27/97             |
| 2) 5.0 KRAD IRRADIATION (0.06 KRADS/HOUR)   | 06/27/97<br>06/30/97 |
| 3) 10.0 KRAD IRRADIATION (0.06 KRADS/HOUR)<br>POST-10.0 KRAD ELECTRICAL MEASUREMENT   | 06/30/97<br>07/02/97 |
| 4) 15.0 KRAD IRRADIATION (0.06 KRADS/HOUR)  | 07/02/97<br>07/03/97 |
| 5) 25.0 KRAD IRRADIATION (0.12 KRADS/HOUR)<br>POST-25.0 KRAD ELECTRICAL MEASUREMENT   | 07/03/97<br>07/07/97 |
| 6) 30.0 KRAD IRRADIATION (0.12 KRADS/HOUR)  | 07/15/97<br>07/17/97 |
| 7) 50.0 KRAD IRRADIATION (0.12 KRADS/HOUR)<br>POST-50.0 KRAD ELECTRICAL MEASUREMENT   | 07/17/97<br>07/23/97 |
| 8) 100.0 KRAD IRRADIATION (0.25 KRADS/HOUR)<br>POST-100.0 KRAD ELECTRICAL MEASUREMENT | 07/23/97<br>07/25/97 |
| 9) 265-HOUR ANNEALING @25°C<br>POST-265 HOUR ANNEAL ELECTRICAL MEASUREMENT            | 07/25/97<br>08/05/97 |
| Effective dose rate = 100,000 RADS/29 DAYS = 143.7 RADS/HOUR = 0.040 RADS/SEC.        |                      |

All parts were irradiated and annealed under bias. See Figure 1

#### CORDRPT2009330.doc

Table III: Electrical Chameteristics of AS58C1001SF

#### **Functional Tests**

| Test# | Test                    | Test Conditions   |
|-------|-------------------------|---|
| 1     | Read Checkerboard       | $V_{CC}$ =4.5V, $V_{IL}$ =0.0V, $V_{IH}$ =4.5V, f=4.9(Hz) |
| 2     | Read Checkerboard       | $V_{CC}$ =5.0V, $V_{IL}$ =0.0V, $V_{IR}$ =5.0V, f=1MHz    |
| 3     | Read Checkerhoard       | $V_{CC}=5.5V$ , $V_{IL}=0.0V$ , $V_{IR}=5.5V$ , f=1MHz    |
| 4     | Write/Read Ones         | $V_{CC}$ =4.5V, $V_{IL}$ =0.0V, $V_{IH}$ =4.5V, f=1MHz    |
| 5     | Write/Read Ones         | $V_{CC}$ =5.0V, $V_{IL}$ =0.0V, $V_{H}$ =5.0V, (=1MHz     |
| 6     | Write/Read Ones         | $V_{CC}=5.5V, V_{IL}=0.0V, V_{HI}=5.5V, f=1MHz$           |
| 7     | Write/Read Zeros        | $V_{CC}$ =4.5V, $V_{IE}$ =0.0V, $V_{1H}$ =4.5V, f=1MHz    |
| 8     | Write/Read Zeros        | $ V_{CC}$ =5.0V, $V_{IL}$ =0.0V, $V_{III}$ =5.0V, f=1MHz  |
| 9     | Write/Read Zeros        | $V_{CC}$ =5.5V, $V_{II}$ =0.0V, $V_{IH}$ =5.5V, f=1MHz    |
| 10    | Write/Read Checkerboard | $V_{CC}=4.5V$ , $V_{H}=0.0V$ , $V_{DI}=4.5V$ , $f=1MHz$   |
| 11    | Write/Read Checkerboard | $V_{CC}$ =5.0V, $V_{1L}$ =0.0V, $V_{1R}$ -5.0V, f=1MHz    |
| 12    | Write/Read Checkerboard | $V_{cc}$ =5.5V, $V_{tt}$ =0.0V, $V_{tt}$ =5.5V, f=1MHz    |

## Parametric Tests

| Test |           |       |                    | Spec. | Lim. |
|------|-----------|-------|--------------------|-------|------|
| #    | Parameter | Units | Test Conditions /1 | min   | max  |
| į    | VOL       | V     | Load = 2.1 mA      | 0     | 0.45 |
| 2    | VOH       |       | Load = -400µA      | 2.4   | 4.5  |
| 3    | IIL       |       | TSTV = 0.0V        | -2.0  | 2.0  |
| 4    | IIL(res_) | μA    | TSTV = 0.0V        | -100  | 100  |
| 5    | ПН        | μΑ    | T\$TV = 5.5V       | -2.0  | 2.0  |
| 6    | JIH(res_) | μA    | TSTV = 5.5V        | -100  | 100  |
| 7    | IOZL      | μΑ    | TSTV = 0.0V        | -2.0  | 2.0  |
| 8    | ЮŽН       | μΑ    | TSTV = 5.5V        | -2.0  | 2.0  |
| 9    | ICC1      | μΑ    | CE = 5.5V          | 0     | 20   |
| 10   | ICC2      | μА    | CE = 2.8V          | 0     | 1000 |
| 11   | ICC3      | mΑ    | Freq. = 1.0MHz     | 0     | 15   |
| 12   | ICC4      | mA    | Freq. = 5.0MHz     | 0     | 50   |
| 13   | TACCLH    | ns    | VCOMP = 2.0V       | 0     | 200  |
| 14   | TACCHL    | ns    | VCOMP = 0.8V -     | 0     | 200  |

#### Note:

<sup>1/</sup> These are the manufacturer's non-irradiated data sheet specification limits. The manufacturer provided no post-irradiation limits at the time the tests were performed.

# TABLE IV: Summary of Electrical Measurements after Total Dose Exposures and Annealing for AS58C1001SF /1

|  |       |      |              |          | [     | Total Dose Exposure (kRads) |              |                |             |       |      |             |         |                  |              |                |  |                                       | Anneshing.   |               |          |
|--|-------|------|--------------|----------|-------|-----------------------------|--------------|----------------|-------------|-------|------|-------------|---------|------------------|--------------|----------------|--|---------------------------------------|--------------|---------------|----------|
| # Functional Tests /2 /3 /4 /5             |       |      |              |          |       | 5.0 10                      |              |                | 1.5         |       |      | 25          |         | 30               |              | 50             |  | 100                                   |              | 265hrs @25°C  |          |
| 1 Vcc=4.5V.Vii=0.0V,Vib=4.5V,Frag=1Milix   |       | 4    |              | P        |       | :: F                        |              | P              |             | P     |      | P           | ,       | P _              |              | P              |  | P                                     |              |               |          |
| 2   Voc=5.0V,VII=0.0V,VII=5.0V,Freq=1MHz   |       | 4    |              | P        |       | P                           |              | . <b>.</b>     |             | P     |      | P           |         | P.               |              | P              |  | P                                     | ļ——          |               |          |
| 3 Vec=5.5V.VII-0.0V.V                      |       |      |              | 6/       | _     | P                           |              | : <b>P</b>     |             | P     |      | P           |         | P                |              | Р              |  | P                                     |              | P             |          |
| 4 Vcc-4.5V,Vii=0.0V,Vik=4.5V,Freq=1MHx     |       | P    |              | P        |       | P                           |              | P              |             | 4P1F  |      | 4PLF        |         | 4P1F             |              | 4PIF           |  | 4P1F                                  |              |               |          |
| 5 Vcc-5.0V,Vb=0.0V,Vb=5.0V,Freq=1MHz       |       | P    |              | <b>P</b> |       | 4P1 <b>T</b>                |              | P              |             | AP1F  |      | 4P1F        |         | 4P1 <b>F</b>     |              | 4P1F           |  | 4P1F                                  | <u> </u>     |               |          |
| 6 Vcc-3.5V,YiI+0.0V,Vab=3.5V,Parq=1MHz     |       |      | . : <b>P</b> | _        | P     |                             | P            |                | Р           |       | 4P1F |             | 4PI₹:   |                  | 4P1 <b>P</b> |                | 4PJF   |                                       | 4P)F         |               |          |
| 7 Vcc-4.5V,YU=0.0V,Y5b=4.5V,Preq=1MHx      |       |      | P            |          | P     |                             | · P          |                | P           |       | 4P1F |             | 4P1F    |                  | 4PLF         |                | 4P1F   |                                       | 4PIF         |               |          |
| 8 Ves=5,0V,VIII-0.0V,VIII=5,0V,Freq=1MIIIs |       |      | P            |          | P     |                             | P            |                | P.          |       | 4PIF |             | 4PIF    |                  | 4P1F         |                | 4PIP   |                                       | 4P1F         |               |          |
| 9 Vcc-5.5V,VH=0.0V,V                       |       | _    |              | P        |       | P                           |              | P              |             | P     |      | 4P1F        |         | 4P1F             |              | 4P1 <b>3</b> * | ļ <u>.                                  </u> | 4P1F                                  | !            | 4P16          | ļ        |
| 10 Ver=4.5V.VB=0.0V.1                      |       | _    |              | P        |       | P. 15                       |              | P              |             | P     |      | P           |         | P                |              | P              |  | P                                     |              | P             |          |
| 11 Vcc-5.0V,Vd=0.0V,VD=5.0V,Freq=150Hz     |       |      | P            |          | P     |                             | : : <b>P</b> |                | P           |       | . p. |             | <b></b> |                  | P            |                | P  |                                       | P            | <u> </u>      |          |
| 12 Vec=5.5V,Vii=0.0V,Vii=5.5V,Fraq=1MHz    |       |      | P. 11.6      |          | P     |                             | P            | ·              | <b>P</b> :- |       | P··· |             | P       |                  | 'P           | <u></u> _      | P  | L <u>.</u>                            | P            | <u> </u>      |          |
| 1,100                                      |       |      | . Line       |          |       |                             |              | <u> </u>       |             |       |      |             |         |                  |              |                |  |                                       |              |               |          |
| * Parameters                               | Units | min  | - EL1        |          |       | 777 . 77                    | ·            | <del>_</del> , |             | <br>  |      | 83          | 1.0     | 82               | 0.8          | B3             | 0.8  | 83                                    | 1.1          | 84            | 1.4      |
| 1 'VOL                                     | mV    | O    | 450          | 94       | 2.6   | 89                          | 0.4          | 88             | 0.8         | 90    | 0,7  | · · · · · · |         | 4.6              | 0            | 4.6            | 0.5  | 4.6                                   |              | 4.6           |          |
| 2 VOH                                      | į v   | 2,4  | 4.5          | 4.4      | 0     | 4.6                         | 0            | 4.6            | 0           | 4.6   | 0    | 4.6         | 0.1     | -3.0             | 0.5          | -3.2           | 1.6  | -3.2                                  | 0.9          | -2.3          | 0.3      |
| 3 IIL                                      | μA    | -2.0 | 2.0          | . 0      | 0     | 0                           | 0            | 0              | 0           | -0.1  | 0.1  | -38.2       | 3.8     | -39.4            | 3.8          | -39.4          | 3.1  | -19.2                                 | 3.5          | -40.4         | 2.       |
| 4 (IL(res_)                                | μΑ    | -100 | 100          | 39.9     | 4.0   | -38.1                       | 3.8          | -38.1          | 3.8         | -36.2 | 3.8  | -36.2       |         | <del>     </del> | 0            | 0.601          | 0.001  | 0.001                                 | 0.001        | 0             | 0        |
| 5 109                                      | μА    | -2.● | 2.0          | i a a    | 0     | 0,                          | 0            | 0              | - 0         | 0     | 0    |             | 0.05    | -0.01            | 0.06         | -0.01          | 0.001  | 0.05                                  | 0.04         | 0.02          | 0.0      |
| 6 EEH(res_)                                | μA    | -100 | 100          | 0.000    | 0,005 | <b>-0.04</b>                | 0.05         | -0.04          | 0.05        | -0.06 | 80.0 | -0.04       |         |                  |              | 0              | 0  | 0.01                                  | 0.44         | 0             | 6        |
| 7 lozL                                     | . д.  | -2.● | 2.0          | 0        | • 1   | 0                           | 0            | 0              | D           | 0     | a    | 0           | - 0     | : · · · · · ·    | - 0          | 0              |  | 0.01                                  | 0            | 0.02          | <u>-</u> |
| 8 IOZH                                     | μA    | -2.6 | 2.0          | 0        | •     | Ò                           | 0            | \$ . 0 . 0.    | D           | 0     | 0    | 0           | 0       | · 8              | 0            |                | <u> </u>                                     | 0.01                                  |              | 0.01          |          |
| 9 ICC1                                     | μА    | 0    | 20           | 0.6      | 7.3   | 0                           | 0            | 0              | 0           | •     |      | Ó           | Ů       | D                | 0            | 0              |  | · · · · · · · · · · · · · · · · · · · |              | ļ             | 6.0      |
| 10 ICC2                                    | pA    | 0    | 1000         | 85       | 0     | 116                         | 7.2          | LHÓ            | 7.2         | 1,14  | 6.7  | 116         | 7.2     | 126              | 11.8         | 129            | 15.7   | 126                                   | - 13.0       | 129           | 0.1      |
| 11 1003                                    | puA   | 0    | 15           | 5.6      | €.1   | 4.6                         | 0.1          | ·) 4.6 ·       | 0.1         | 4,5   | 0.1  | 4.5         | 0.1     | 4.5              | 0.1          | 4.5            | 0.1  | 4.4                                   | ●.1<br>●.2   | 26.9          | 0.2      |
| 12 JCC4                                    | шA    | O.   | 50           | 29,3     | €.6   | . 27,4                      | 0.3          | 27.4           | 0.4         | 27,4  | 0.3  | 27,4        | 0.4     | 27.3             | 0.3          | 27.2           | 0.3  | 26.9                                  | <del></del>  | <del></del> - | ŧ        |
| 13 TACCLH                                  | .03   | 0    | 200          | 67.9     | 1.1   | 66.4                        | 4.0          | 68.4           | 0.3         | 69.0  | 0.3  | 68.7        | 0.3     | 68.9             | 0.2          | 68.9           | 0.3  | 69.9                                  | <b>9,2</b> - | 70.0          | 0_       |
| 14 TACCHL                                  | 0.5   | 0    | 200          | 54.8     | 0.6   | 54.5                        | 0.5          | 54,7           | 0.6         | 55.3  | 0.8  | 54.6        | 0.8     | 54.8             | 0.8          | 54.6           | 0.8  | 55.3                                  | 9.8          | 56.4          | 0.8      |

#### Notes:

- 17 The mean and standard deviation values were estimated over the four parts irradiated in this testing. The control sample remianed constant throughout the testing and is not included in this table.
- 2/ These are the manufacturer's pre-irradiation data sheet specification limits. No post irradiation limits were provided by the manufacturer at the time these tests were performed.
- 3/ "P" ("F") indicates that all parts passed (failed) this test at this irradiation or annealing level. "aPmP" indicates that it parts passed and in parts failed this test at this irradiation or annellaing step.
- 4/ The limits for all functional tests are: VOL < 1.5V and VOH > 1.5V. Funct. 1-3: Read Checkerboard, Funct. 4-6: W/R Zeroes, Funct. 7-9: W/R Ones, Funct. 10-12: W/R Checkerboard.
- 5/ SN75 is included in the functional test portion of the table for comparison only. It is not included in the parametric test results because the parametric measurements for this part were very erratic.
- 6. This test was not performed at this level, the memory had no data stored in it initially.

Radiation Sensitive Parameter: 11L.

7